

```

# *****
# *** Configuration file for EMERGE initialization ***
# ***
# *** General Rules: ***
# *** Commands are not case sensitive (upper or lower case). ***
# *** Commands can not be continued to next line. ***
# *** #/blank - Line is treated as a comment (no action). ***
# *** Commands are in sections. Sections begin with a name ***
# *** enclosed in square brackets [] and end when another ***
# *** section begins. ***
# *** Keyword commands have unique meaning only within a ***
# *** section. ie: A keyword may have different meaning ***
# *** depending on what section it is in. ***
# *** Keyword commands before the first section are ***
# *** ignored. ***
# ***
# *** Primary Commands: ***
# *** [control] - Must be first section! ***
# *** Real=nK,h Specifies non-virtual memory ***
# *** pool size and maximum number of ***
# *** handles to provide for. ***
# *** Virtual=nK,b Specifies virtual memory pool ***
# *** size and block size. Pool size ***
# *** must be multiple of block size. ***
# *** Swap=file,iK,mK,h Specifies swap file name, ***
# *** initial/min size, Maximum size, ***
# *** & initial number of handles. ***
# *** Module=name,Program=pgm.ext,Overlay=n[,Config=cfg.ext ***
# *** Specifies an Emerge-loadable ***
# *** module and assigns a logical ***
# *** "name", program file name, ***
# *** overlay area number, and ***
# *** configuration program file name. ***
# *** name = limited to 12 bytes. ***
# *** pgm.ext = limited to 12 bytes ***
# *** cfg.ext = limited to 12 bytes ***
# *** Debugger=pgm.ext [opts] ***
# *** Specifies optional debugger to ***
# *** use during development. ***
# ***
# ***
# *****

```

[control]

```

# ***** Memory buffers
# *****
Real=12K,75 # 12K buffer, 75 Handles
Virtual=5K,256 # 5K buffer, 256-byte blocks
Swap=C:\TEMP\EMSWAP. $$$,32K,128K,100 # File, 32K init size, 128K Max,
100 hdls
MSG=EMERGE.MSG,ERROR,CON

```

Module=REDIRECTOR,Program=EMREDIR.EXE,Overlay=1,Config=RDRCONFIG.EXE

Module=KEYWORD, Program=EMKEYWD.EXE, Overlay=2, Config=KW_CF.EXE
Module=HP, Program=EM_HP.EMU, Overlay=3, Config=EMUHP_CF.EXE
Module=POPUP, Program=EMPOPUP.EXE, Overlay=3
Module=DEVICE, Program=EM_HP.DRV, Overlay=4, Config=DEVHP_CF.EXE

[REDIRECTOR]

TIMEOUT=# (seconds to timeout for input data)
BUFFER=# (size of input print data buffer)
LPT=# (logical printer number: 1, 2, or 3)
SCANCODE=# (Popup hotkey scan code)
SHIFTCODE=# (Popup hotkey shift code)
HANDLES=# (size of DOS file handle table)

TIMEOUT=15

BUFFER=256

LPT=1

SCANCODE=1

SHIFTCODE=8

HANDLES=40

[KEYWORD]

HORZ-UNITS=# (units for grid coordinates * 100)
VERT-UNITS=# (units for grid coordinates * 100)
PRINT-ERRLOG=# (FormDriver=0, EOJ=1, JOB=2)
START-EMUL= (Beginning data format (emulation) type)

HORZ-UNITS=1000

VERT-UNITS=600

PRINT-ERRLOG=0

START-EMUL=HP

[HP]

MAX-FONTS=# (# of fonts to manage in table)
MAX-MACROS=# (# of macros to manage in table)
MISSING-GLYPH=# (Replace with Space=1, BadGlyph=2, Ignore=3)
MACRO-BLOCK=# (# of bytes for block of pag. mem. to allocate for macro)

FULL=# (logical dpi for full size printing)

STANDARD=# (logical dpi for standard size printing)

PARSE-STRING=# (# of bytes allocated for parsing single command)

PARM-STRING=# (# of bytes allocated for parsing single parameter)

SPACE-NOT_DATA (if set, spaces are not treated as data for page ejects)

MAX-FONTS=64

MAX-MACROS=20

MISSING-GLYPH=1

MACRO-BLOCK=256

FULL=300

STANDARD=282

PARSE-STRING=32

PARM-STRING=32

SPACE-NOT_DATA=0

[DEVICE]

INTERFACE={LPT# | COM# | VIRTUAL |
FILE[,print.dat]}[, {DIRECT[,XONXOFF] | BIOS}]

```
# PRINTER=#[,Description]
# MAX-FONTS-PER-PAGE=#
# MEMORY=Printer memory (KB)
# SIZING=Printer font memory sizing values.
# TIMEOUT=# (# = ticks at approx 18.2/sec) Default: 1080
# HORZ-ADJUST=# (# = dot adjustment for difference between non-
printable
# left margin and grid coordinates)
# Examples:
# Interface=FILE
# Interface=FILE,pcl.dat
# File name is created on CONFIG.FD temporary path!
# Interface=LPT1,BIOS
# Interface=LPT1,DIRECT
# Interface=COM1,BIOS
# Interface=COM1,DIRECT
# Interface=COM1,DIRECT,XONXOFF

Interface=LPT1,BIOS
Printer=3,LaserJet III
Max-Fonts-Per-Page=72
Memory = 2048
Sizing = 1024,1,2,512,256
Timeout=1638
HORZ-ADJUST=15
```

□